


肖特基整流二极管

※ NSD-B5817W~B5819W (SOD-123)



SOD-123



➤ 额定值

| Parameter | Symbol | NSD-B5817W | NSD-B5818W | NSD-B5819W | Unit |
|--|--------------------|------------|------------|------------|------|
| Non-Repetitive Peak Reverse Voltage | Vrm | 20 | 30 | 40 | V |
| Peak Repetitive Peak Reverse Voltage Working Peak Reverse Voltage DC Blocking Voltage | Vrrm VrwM Vr | 20 | 30 | 40 | V |
| RMS Reverse Voltage | Vr(rms) | 14 | 21 | 28 | V |
| Average Rectified Output Current | Io | | 1 | | A |
| Peak Forward Surge Current @t=8.3ms | Ifsm | | 9 | | A |
| Repetitive Peak Forward Current | Ifrm | | 1.5 | | A |
| Power Dissipation | Pd | | 500 | | mW |
| Thermal Resistance Junction to Ambient | RbjA | | 200 | | °C/W |
| Junction temperature | Tj | | I ZD | | °C |
| Storage Temperature | Tstg | | -55~+150 | | |

➤ 电性能

| Parameter | Symbol | Test conditions | Min | Max | Unit |
|---------------------------------|--------|---|----------------|---------------|------|
| Reverse breakdown voltage | V(BR) | Ir= 1mA NSD-B5817W NSD-B5818W NSD-B5819W | 20 30 40 | | V |
| Reverse voltage leakage current | Ir | Vr=20V NSD-B5817W Vr=30V NSD-B5818W Vr=40V NSD-B5819W | | 1 | mA |
| Forward voltage | Vf | NSD-B5817W If=1A If=3A | | 0.45 0.75 | V |
| | | NSD-B5818W If=1A If=3A | | 0.55 0.875 | V |
| | | NSD-B5819W If=1A If=3A | | 0.6 0.9 | V |
| Diode capacitance | Cd | Vr=4V, f=1MHz | | 120 | pF |

➤ 特性曲线

